



V1000 Foetal Heart Simulator

The V1000 foetal heart simulator is a hand held device that has been designed for use by engineers, midwives and clinicians.

To be used with foetal heart monitors and transducers for:

- Testing prior to use
- Fault finding and diagnosis
- Soak testing
- Simulation and training
- Use as part of a PPM procedure
- Verification of correct chart paper installed



This unique patented simulator is easy to use and offers objective testing of foetal heart monitors; rather than subjective traditional methods, or cumbersome and expensive test equipment.

V1000 Foetal Heart Simulator

Modes of operation

Manual selection of BPM (foetal heart rate). Starting at 120 BPM each press of the foetal heart rate button selects the following rate levels in turn, 120, 150, 180, 210, AUTO, 30, 60, 90.

Automatic selection of BPM (foetal heart rate). This consists of a cyclic test routine of a 30 second period at each heart rate level of 30, 60, 90, 120, 150, 180 and 210 BPM.

Accuracy

< 1 bpm

Controls

On/Off

Foetal heart rate (beats/minute) selector

Intensity control

Indicators

BPM (beats per minute) Auto, 30, 60, 90, 120, 150, 180, 210

Low battery

Batteries

4 x 1.5V AA/MN1500/LR6 alkaline batteries

Dimensions

228mm (l) x 72mm (w) (117mm (w) max) x 47mm (h)

Weight

400g (with batteries)

V1000 Foetal Heart Monitor Part No. 1410000

Optional Accessories

Wall mounting bracket Part No. 1420000

Case Protector Part No. 1420001

Carrying Case Part No. 0013110

Service Part No. 1480000

Warranty

12 months

IP Rating

IP41

Specifications subject to change



V1000 on wall mounting bracket



V1000 in case protector



V1000 in carrying case

CE

Distributed by:



VIAMED

Viamed Limited • 15 Station Road • Cross Hills
Keighley • West Yorkshire • BD20 7DT • United Kingdom
Tel: +44 (0)1535 634542/636757 Fax: +44 (0)1535 635582
Email: info@viamed.co.uk Website: www.viamed.co.uk



FS 28344 MD 78787

BS EN ISO 9001-2000
ISO13485-2003