

# MNOLO CiTiceL®

ppb Nitric Oxide (NO) Gas Sensor Part Numbers: AB770-440 (without bias board) AB770-40Z (with Bias Board)

## **Product** Data Sheet

## **Product Datasheet**

**MNOLO Nitric Oxide Sensor** 

## **Document Purpose**

The purpose of this document is to present the performance specification of the MNOLO Nitric Oxide gas sensor.

This document should be used in conjunction with the Operating Principles (OP16).

The data provided in this document are valid at 20°C, 50% RH and 1013 mBar for 3 months from the date of sensor manufacture.

Output signal can drift below the lower limit over time. For guidance on the safe use of the sensor, please refer to the Operating Principles (OP16).

Doc. Ref.: mnolo.indd ECN I 5097 Issue 4

Web: www.citytech.com Email: sales@citytech.com Call: +44(0) 23 9228 8100

10th September 2018

Page 1 of 3





## MNOLO CiTiceL®

ppb Nitric Oxide (NO) Gas Sensor Part Numbers: AB770-440 (without bias board) AB770-40Z (with Bias Board)

## **Product** Data Sheet

**Key Features & Benefits:** 

- A robust ppb NO sensor suitable for breath analysis
- · Allows measurement with simpler sample preparation
- Industry standard 7-Series package

## Technical Specifications

#### **MEASUREMENT**

Operating Principle | 4-electrode electrochemical

Measurement Range | 0-300 ppb NO Maximum Overload

500 ppb NO Filter To remove acid gases

**Sensitivity** 0.7 - 1.7 nA/ppb (see note)

7 - 17 mV/ppb when used with recommended circuitry

Zero Offset 0-100 ppb NO equivalent ± 3000 mV

Baseline

Repeatability Linearity

Start-up Time from Open Circuit | <24 hours to fully stabilise (See Operating Principles) NO response is linear but may be influenced by the humidity

zero offset

#### **ELECTRICAL**

Bias Voltage | +350 mV

Resolution ±5% of linear region (above

zero offset level) when using recommended circuitry

#### **MECHANICAL**

Housing Material | 20% glass filled polypropylene

Colour | White

Weight 16g (approx.)

Orientation | Any

#### **ENVIRONMENTAL**

**Operating Temperature Range:** 

**Typical Applications** | Breath Analysis

Continuous 10°C to 30°C Intermittent | 0°C to 35°C

Operating Pressure Range | 1 atm ± 10%

Operating Humidity Range:

Continuous | 25% to 75% RH non-condensing Intermittent | 0% to 100% RH non-condensing

### **INTRINSIC SAFETY DATA**

Maximum at 1000 ppb | 0.1 mA Maximum o/c Voltage | 1.3 V Maximum s/c Current | <1.0 A

#### **LIFETIME**

(at constant temp, pressure & RH) City Technology for further details

Long Term Output Drift | May depend on usage. Contact


Recommended Storage Temp | 10°C to +30°C


Expected Operating Life | >2 years from date of manufacture

**Storage Life** 6 months in sealed container

### **Product Dimensions**







All dimensions in mm All tolerances ±0.15 mm unless otherwise stated

**IMPORTANT NOTE:** All measurements were taken at 20°C and 50% ambient RH. 20% sampling RH at ambient pressure with a sampling time of 15 seconds unless otherwise stated. The sensors were monitored on a City Technology proprietary low noise potentiostatic circuit, a copy of which is available on request. The performance data detailed in this document refers to new sensors.

For sensor performance data under other conditions, refer to the Operating Principles.

Performance characteristics outline the performance of sensors supplied within the first 3 months. Output signal can drift below the lower limit over time.

Doc. Ref.: mnolo.indd ECN I 5097 Issue 4 10th September 2018

Page 2 of 3





# MNOLO CiTiceL®

ppb Nitric Oxide (NO) Gas Sensor Part Numbers: AB770-440 (without bias board) AB770-40Z (with Bias Board)

## **Product** Data Sheet

## **Poisoning**

CiTiceLs electrochemical sensors are designed for operation in a wide range of environments and harsh conditions. However it's important that exposure to high concentrations of solvent vapours is avoided, both during storage, fitting into instruments, and operation. When using sensors with printed circuit boards (PCBs), degreasing agents should be used before the sensor is fitted. Do not glue directly on or near the sensor as the solvent may cause crazing of the plastic.

### **Cross Sensitivity Table**

Whilst CiTiceLs are designed to be highly specific to the gas they are intended to measure, they will still respond to some degree to various other gases. The table below is not exclusive and other gases not included in the table may still cause a sensor to react.

IMPORTANT NOTE: The cross sensitivity data shown below does not form part of the product specification and is supplied for guidance only. Values quoted are based on tests conducted on a small number of sensors and any batch may show significant variation. For the most accurate measurements, an instrument should be calibrated using the gas under investigation.

Gas	Concentration Used	Reading (ppb equivalent)
Nitrogen, N <sub>2</sub>	100%	-0.05
Carbon Dioxide, CO <sub>2</sub>	1.12%	17.3
Carbon Monoxide, CO	45 ppm	17.6

Test criteria: Baseline gas 50% RH NO filtered air

Cross sensitive gas 0% RH

Cross sensitivity data was calculated reference to the standard regime (baseline 50%Rh filtered cylinder air, 50 & 100 ppb NO @ 20% RH). Due to the effect of RH on the MNO-LO sensor, cross sensitivities have been determined using 0%RH test gas.

#### SAFETY NOTE

This sensor is designed to be used in safety critical applications. To ensure that the sensor and/or instrument in which it is used, are operating properly, it is a requirement that the function of the device is confirmed by exposure to target gas (bump check) before each use of the sensor and/or instrument. Failure to carry out such tests may jeopardize the safety of people and property.

Every effort has been made to ensure the accuracy of this document at the time of printing. In accordance with the company's policy of continued product improvement City Technology Limited reserves the right to make product changes without notice. The products are always subject to a programme of improvement and testing which may result in some changes in the characteristics quoted. As the products may be used by the client in circumstances beyond the knowledge and control of City Technology Limited, we cannot give any warranty as to the relevance of these particulars to an application. It is the clients' responsibility to carry out the necessary tests to determine the usefulness of the products and to ensure their safety of operation in a particular application.

Doc. Ref.: mnolo.indd ECN I 5097 Issue 4

10th September 2018

Page 3 of 3

