3-4-00 FIRST GO, COMMENTS PLEASE. 2 xPTNO MISSING STANEH. This is the 14 Dnaft for the Constructs of the TAOOR (0310000) 0 5 APR 2000

#### Cabinet Assembly.

Parts required..

1\*Resus cabinet either (Pt No 0330005 or 0330105)

1\*Bed base (Pt No 0320020 or ?))

1\*Bed Mattress (Pt No 00320035 or 0320005)

6\*Srews (Pt No 0330065)


1\*Tom Thumb.

6\*Viamed sticky labels

1\*Viamed logo label.

1\*patient circuit (Pt No 035005)

3\*Drawers (Pt No 0310020)



- Fit bed base (Pt No 0320020 ) to drop down front panel ,300mm from bottom of front panel and 50mm from the left hand side whilst looking into cabinet, using 6 screws (Pt No 0330065). Check that mattress (Pt No 0320035 ) is the correct size for the bed.
- 2. Fit Viamed logo sticker (Pt No ) to top left hand front corner of cabinet surround. So that it can be seen when front panel closed up.
- 3. Fit Viamed sticky labels to rear of suction unit and clock.
- 4.Remove CE label from the front of cabinet carefully and refix it to the bottom of the right hand side of the cabinet about 1cm from the front and 3cm from the bottom, place Viamed sticky label just below it.
- 5.Last Viamed sticky label to be fitted inside the cabinet 1cm above the top mounting rail and half its length.
- 6. Locate 3 drawers (Pt No 0310020 ) and put onto mountings on the right side oif the cabinet. Add patient circuit (Pt No 035005)
- 7.Fit completed timer, Suction assembly and Tom Thumbinto cabinet together with suction jar and check everything looks straight and that door closes.
- 8. Check that unit is clean and free of scratches.



Completed Cabinet with all parts fitted.

#### Clock Assembly for Cabinet.



Parts required for clock assembly

1\*Time Elapsed clock (Pt No 0310010)

1\*Timer bracket (Pt No 0330020)

1\* Dovetail (Pt No 0330030)

2\*Washers (Pt No 0330080)

2\*Bolts (Pt No 0330070)

2\*Nuts (Pt No 0330075)

2\*Bolts (Pt No 0330085)


1\*Rail bracket (Pt No 03200103)

Remove two small Screws holding clock to base.



Using the parts shown assemble the clock mounting brackets.


- Using clock bracket (Pt No 0330020) fix dovetail (Pt No 0330030) to it using bolts (Pt No 0330070), Nuts (Pt No 0330075) and washers on plate side (Pt No 0330080), Make sure dovetail has its narrow side to Bracket.
- 2. Fix clock to bracket using screws (Pt No 0330085) into holes in base of clock where original clock base was fitted.
- 3. Fit complete assembly to rail bracket (Pt No 0320010)then to cabine and check that clock is straight.






Rail bracket, Pt No 0320010...





Completed assembly with rail clamp.

### Oxylitre Suction Assembly



Parts required for Oxylitre suction assembly

1\*Bracket (Pt No 0330100)

2\*Srews (Pt No 0330065)

2\*Spacers (Pt No 0330093)

1\*Bracket (Pt No 0330060)

4\*Washers (Pt No 0330080)

2\*Screws (Pt No

1\*Suction Jar (Pt No 0320030)

!\*Suction Hose (Pt No 0330015)


1 metre of clear tubing (Pt No 0330035)



- 1. Remove both screws from rear of suction unit and put to one side.
- 2. Fit bracket (Pt No 0330100) to rear of suction unit over the inlet connection using spacers (Pt No 0330095), screws (Pt No 0330065) and washers (Pt No 0330080).
- 3. Using screws (Pt No?) And washers (Pt No 0330080) fit mounting clamp to bracket (Pt No 0330100). Screws will go directly into bracket as hloes are threaded.
- 4. Put 1\* metre of suction tubing with unit
- 5. Check suction hose fits correctly to suction unit.





Suction Jar (Pt No 0320039 ).



Suction Hose (Pt No 0330015).


## Cabinet Labels and Logo.





Viamed Label

Front of abinet



Viamed Label.

# Parts list for Cabinet

Qty	Description	Pt No
1 2 2 1 1 1 1 2 2 2 2 1 1 1 1 6 1 6 1 6	Bracket Screws Spacers Bracket Washers Screws Suction jar Suction Hose Clear tubing Time elapsed clock Timer bracket Dovetail Washers Bolts Nuts Bolts Rail bracket Cabinet Bed base Mattress Screws Tom Thumb Viamed address labels Viamed Logo Patient circuit Drawers Suction unit (Oxylitre) or (East)	0330100 0330065 0330093 0330080  M5 ½ inch 0320030 0330015 0330035 0310010 0330020 0330030 0330080 0330075 0330085 0320103 0330005 or 0330105 0320020 or 0320035 or 0320005 or 0320040 0330065  Various
	or (Therapy Equipment)	0310005